

G E A R E D	减速比 K Gear Ratio	56	
	额定电压 V Rated Voltage	12	
	空载转速 RPM Free-load Speed	143±10%	
	空载电流 mA Free-load Current	390 max	
	额定转速 RPM Rated Speed	114±10%	
	额定电流 mA Rated Current	1700 max	
	额定扭矩 kgf.cm Rated Torque	5.5	
	堵转电流 mA Stall Current		
	堵转扭矩 kgf.cm Stall Torque		
	是否可堵转 Stall allowed or not	NO	
转向 CW/CCW Direction	CCW		
噪音 dB Noise (L=300mm)			
M O T O R	驱动电机型号 Driving Motor Model	395	
	电机空载转速 RPM Free-load Speed	6000±12%	
	电机空载电流 mA Free-load Current	300 max	
	轴向间隙 mm End Play	0.5 max	